



IGBT Power Module 1200V/200A

Features

- ◆ 62mm Fast Switching Trench / Field Stop IGBT Technology
- ◆ Low Switching Losses
- ◆ Super Fast Diodes
- ◆ High Short Circuit Capability


Preliminary

Applications

- ◆ Welder / Power Supply
- ◆ UPS / Inverter
- ◆ Industrial Motor Drive





Circuit Diagram Headline



Maximum Ratings (T_c=25°C)

Item	Symbol	Rated Value	Unit
Collector-Emitter Voltage	T _{VJ} = 25°C V _{CES}	1200	V
Gate-Emitter Peak Voltage	V _{GES}	±20	V
Continuous DC Collector Current	T _c = 100°C T _c = 25°C I _{C,nom.} IC	200 320	A
Repetitive Peak Collector Current	t _p = 1ms I _{CRM}	400	A
Total Power Dissipation	P _{tot}	1100	W
Isolation Voltage (Terminal to Base, AC 1 min.)	V _{iso}	3000	V
Continuous DC Forward Current	I _F	200	A
Repetitive Peak Forward Current	t _p = 1ms I _{FRM}	400	A
Temperature under switching conditions	T _{VJ op}	-40 ~ +150	°C
Storage Temperature	T _{stg}	-40 ~ +125	°C
Mounting Torque	Module Base to Heatsink (M6)	3~6	N.m
	Busbar to Terminal (M6)	2.5~5	

Package Outlines



Dimensions in mm (1 mm = 0.0394")



■ Electrical Characteristics ($T_{vj} = 25^{\circ}C$)

Characteristic		Symbol	Test Conditions	Min.	Typ.	Max.	Unit
Collector-Emitter Cut-Off Current		I_{CES}	$V_{CE} = 1200V$ $V_{GE} = 0V$	-	-	5.0	mA
Gate-Emitter Leakage Current		I_{GES}	$V_{GE} = 20V$ $V_{CE} = 0V$	-	-	400	nA
Collector-Emitter Saturation Voltage		$V_{CE(sat)}$	$I_C = 200A, V_{GE} = 15V$	-	1.75	2.15	V
Gate Threshold Voltage		$V_{GE(th)}$	$V_{CE} = V_{GE}, I_C = 7.6mA$	5.2	5.8	6.4	V
Input Capacitance		C_{ies}	$V_{CE} = 25V, V_{GE} = 0V, f = 1MHz$	-	29	-	nF
Reverse Transfer Capacitance		C_{res}	$V_{CE} = 25V, V_{GE} = 0V, f = 1MHz$	-	0.5	-	nF
Switching Time	Rise Time	t_r	$V_{CE} = 600V$ $I_C = 200A$ $R_G = 2.4\Omega$ $V_{GE} = \pm 15V$	-	0.08	-	μs
	Turn-On Time	$t_{d,on}$		-	0.24	-	
	Fall Time	t_f		-	0.06	-	
	Turn-Off Time	$t_{d,off}$		-	0.46	-	
Turn-on Energy Loss Per Pulse		E_{on}	$I_C = 200A, V_{CE} = 600V, L_S = 30nH$ $T_{vj} = 25^{\circ}C$ $V_{GE} = \pm 15V, R_{Gon} = 2.4\Omega$ $T_{vj} = 125^{\circ}C$ $di/dt = 4000A/\mu s$ ($T_{vj} = 150^{\circ}C$) $T_{vj} = 150^{\circ}C$	-	4.0 9.0 11.0	-	mJ
Turn-off Energy Loss Per Pulse		E_{off}	$I_C = 200A, V_{CE} = 600V, L_S = 30nH$ $T_{vj} = 25^{\circ}C$ $V_{GE} = \pm 15V, R_{Goff} = 2.4\Omega$ $T_{vj} = 125^{\circ}C$ $du/dt = 4500V/\mu s$ ($T_{vj} = 150^{\circ}C$) $T_{vj} = 150^{\circ}C$	-	14 20 23	-	mJ

■ Free Wheeling Diode Ratings & Characteristics ($T_{vj} = 25^{\circ}C$)

Characteristic		Symbol	Test Conditions	Min.	Typ.	Max.	Unit
Forward Voltage		V_F	$I_F = 200A, V_{GE} = 0V$	-	2.0	2.15	V
Peak Reverse Recovery Current		I_{RM}	$I_F = 200A, V_R = 600V$ $T_{vj} = 25^{\circ}C$ $V_{GE} = -15V$ $T_{vj} = 125^{\circ}C$ $-di_F/dt = 4000A/\mu s$ ($T_{vj} = 150^{\circ}C$) $T_{vj} = 150^{\circ}C$	-	144 160 170	-	A
Recovered Charge		Q_r	$I_F = 200A, V_R = 600V$ $T_{vj} = 25^{\circ}C$ $V_{GE} = -15V$ $T_{vj} = 125^{\circ}C$ $-di_F/dt = 4000A/\mu s$ ($T_{vj} = 150^{\circ}C$) $T_{vj} = 150^{\circ}C$	-	13.6 25.0 34.0	-	μC
Reverse Recovery Energy		E_{rec}	$I_F = 200A, V_R = 600V$ $T_{vj} = 25^{\circ}C$ $V_{GE} = -15V$ $T_{vj} = 125^{\circ}C$ $-di_F/dt = 4000A/\mu s$ ($T_{vj} = 150^{\circ}C$) $T_{vj} = 150^{\circ}C$	-	8.0 15.0 16.5	-	mJ

■ Thermal Characteristics ($T_C = 25^{\circ}C$)

Characteristic		Symbol	Test Conditions	Min.	Typ.	Max.	Unit
Thermal Resistance	IGBT	$R_{th(j-c)}$	Junction to Case	-	-	0.135	K/W
	Diode			-	-	0.200	



Typical Characteristics

Preliminary Data

Fig.1 Output characteristic IGBT, Inverter (typical)




Fig.2 Output characteristic IGBT, Inverter (typical)




Fig.3 Transfer characteristic IGBT, Inverter (typical)




Fig.4 Switching losses IGBT, Inverter (typical)




Fig.5 Switching losses IGBT, Inverter (typical)




Fig.6 Transient thermal impedance IGBT, Inverter




Fig.7 Reverse bias safe operating area IGBT, Inverter (RBSOA)





Fig.8 Forward characteristic of Diode, Inverter (typical)





Typical Characteristics

Preliminary Data

Fig.9 Switching losses Diode, Inverter (typical)




Fig.10 Switching losses Diode, Inverter (typical)





Fig.11 Transient thermal impedance Diode, Inverter





Disclaimer

DACO Semiconductor reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein.

DACO Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does DACO Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages.

Purchasers is responsible for its products and applications using DACO Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by DACO Semiconductor. "Typical" parameters which may be provided in DACO Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts.

DACO Semiconductor products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of DACO Semiconductor's product can reasonably be expected to result in personal injury, death or severe property or environmental damage. DACO Semiconductor accept no liability for inclusion and/or use of DACO Semiconductor's products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Purchasers buy or use DACO Semiconductor products for any such unintended or unauthorized application, Purchasers shall indemnify and hold DACO Semiconductor and its suppliers and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that DACO Semiconductor was negligent regarding the design or manufacture of the part.

No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of DACO Semiconductor Co., Ltd.